



MFX-2035

High performance A3 business Copier, Printer and Scanner with low total cost of ownership



Scan

Print

Network

Copy



Specifications

Maximum Scan / Print size:	A3
Print Speed :	20 ppm (A4 LEF)
User Interface :	5-line LCD
Automatic Document Feeder :	Optional ADF (50 sheets) / RADF (100 sheets)
Paper Capacity :	300 sheets (includes 50 sheets bypass tray)
Maximum Paper Capacity :	1,800 sheets
Duplex Printing :	Option
Quad Access :	Yes
Ethernet :	Optional 10/100 BaseT, RJ-45 connection
Network Protocol :	Optional TCP/IP
Local Connection :	USB 2.0
Easy Change Consumables :	Yes, front loading
Printing Method :	Electrophotographic printing/LED
Scanning Method :	Mono CCD
Dimensions :	583mm (W) x 629mm (D) x 426mm (H)
Power :	220-240 VAC, 50/60Hz
Weight :	Approx. 30.0kg

General Features

20 ppm print engine

- Output printing at speed up to 20 pages per minute.

Optional document feeder

- Enables copying or scanning of large jobs without having to separate them into multiple sets.

Flexible paper capacity

- Standard 300-sheets paper capacity easily expands to 1,800 sheets with optional cassette.

Multipurpose bypass tray

- 50 sheet bypass tray enables you to copy onto OHP film, letterhead or envelopes while electronic sorting lets you manage output more easily.

USB B/W scanning is standard

- High-resolution scanner offers easy digital transfer of hardcopy photos, charts and various office documents. TWAIN compliance scans images into popular software applications.

Optional duplex print

- Optional duplex unit enables you to copy on two sides of the paper.

Card copy

- You can copy the front and back of ID-cards, cheques, and custom size documents so that both sides are printed together on a single page.

Combine copy

- You can copy a multiple page document onto a single page to reduce print cost.

Standard GDI-based printing

- GDI printing system produces crisp, clear prints at 600dpi.

Optional PCL printer (PCL 5e/XL)

- GDI printer can be upgraded to a PCL printer allowing compatibility with corporate and legacy applications.

Features

Copier Features:

Copy Speed	20 cpm (A4 LEF)
First - copy - out Time (FCOT)	4.8 seconds (Using A4LEF from 1st cassette)
Warm Up Time	5 seconds (at 20°C room temperature)
Copy Quantity	1 - 999
Maximum Resolution	600 x 600dpi
Memory	128MB
Reduction / Enlargement	25 - 200% (1% step)
Card copy	Yes
Combine copy	Yes (2 / 4 / 8 in 1)
Repeat copy	Yes (2 / 4 / 8 repeat)
Series copy (Book copy)	Yes (A3 → A4 x2)
Electronic Sorting	Yes
Duplex copy	Option

Scanner Features:

Scan Method	Mono scanner
Protocol	TWAIN
Interface	USB 2.0(Std.) / 10BASE-T,100BASE-TX(Op.)
Scan Resolution	600 x 600dpi, 300 x 300dpi, 200 x 200dpi
Greyscale	256 levels
Reduction / Enlargement	50 - 200% (1% step)

Printer Features:

Emulation	GDI (Standard) / PCL 5e, XL (Option)
Interface	USB 2.0(Std.) / 10BASE-T,100BASE-TX(Op.)
Operating System	Windows 2000, XP, VISTA, 7, 8, Windows Server 2003 / 2008 / 2012
Print Quantity	1 - 999
Reduction / Enlargement	25 - 400% (1% step)
Combine print	Yes (2 / 4 / 8 in 1)
Duplex print	Option

Consumables:

Toner Yield	11,000 sheets (A4 @ 5%)
Drum Life	100,000 sheets (A4 1-page cycle)

Options:

ADF	50 sheets(A4): Simplex Document Feeder
RADF	100 sheets(A4): Duplex Document Feeder
Duplex print	Duplex print kit
Paper Tray (S)	Optional Cassette 250 sheets
Paper Tray (L)	Optional Cassette 500 sheets
Network Interface (NP-800)	10BASE-T / 100BASE-TX interface card
PCL Printer Interface	PCL 5e & XL emulation

Muratec reserve the right to change design, features and specification details without prior notice. Windows, Windows Server are registered trademarks of the Microsoft Corporation.

Network connectivity

The MF-X2035 will also perform as a network printer. Just add the optional Network Interface Card (NP-800), and you can print black and white documents via your network from Windows 2000, XP, Vista, 7, 8 and Server 2003/2008/2012. You can also use TWAIN scan via network with NP-800.



Caution for Safety

- Please read the instruction manual carefully before using the machine.
- DO NOT use the machine in wet, humid, dusty, and/or smoky environment. Such environment may cause fire, malfunction and/or electric shock.

MURATA MACHINERY, LTD.
136, Takeda-Mukaishiro-cho, Fushimi-ku, KYOTO 612-8686 JAPAN
TEL:81-75-672-8243 FAX:81-75-672-8142
<http://www.muratec.co.jp>

MURATA MACHINERY, LTD., DUBAI BRANCH
P.O.Box 61105 Jebel Ali Dubai UAE
TEL:971-4-8817409 FAX:971-4-8817412
<http://www.muratec.net/ce/>